



| MODEL | | NovoCast NC1000 |
|--------------|------------------------------------|--|
| BYOD | BYOD - Supported OS | Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, iOS 11.0 and above, Android 5.0 and above |
| | | Screen Mirroring for iOS and Android |
| | | Miracast not supported |
| | Split Screen | Up to 2, side by side |
| | Mirroring Resolution | Up to 1080p, 30 fps |
| | Output Resolution | 1080p (1920 x 1080), 720p (1280 x 720) |
| FEATURES | Collaboration | Windows 10 Extended Desktop function, Moderator function, AirNote for instant annotation from meeting participants, Novo Screennote for virtual whiteboard |
| | Productivity | QR Code connection support, PIN connection function |
| | Digital Signage Announcement Board | NA |
| | Wireless Screen Duplication | NA |
| | Security | Dual network WiFi & LAN, AES-256 encryption, Kensington lock |
| CONNECTIVITY | WiFi | 802.11ac, b/g/n, 2.4GHz & 5GHz 1T1R with 1 external antenna |
| | Output | HDMI-Out Audio-Out (3.5mm jack) |
| | Input | USB Type A; microSD Slot; DC Jack Power-In |
| SYSTEM | CPU | Quad-core ARM |
| | Storage | 8GB |
| GENERAL | Power | Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/2A. Consumption: 10W |
| | Product Dimensions (L x W x H) | 100 x 100 x 20 mm |
| | Weight (Net) | 184 g |
| | What's Included | Main Unit, Antenna, HDMI Cable, USB Cable, Power Adapter, USB to Ethernet Adapter, Wall Mount KIT, Document KIT |
| | Optional Accessory | NA |
| | Warranty | 3 Years |

v03kpo